



PeopleLink Multichannel All in one DSP



PeopleLink DSP is the ultimate choice for High Definition Audio signal processor. The most powerful HD audio available, it delivers full continuous presence meetings with Multi Location Voice conferencing over its 4 inputs and 2 output DSP, ideal for local sound reinforcement. Highly scalable and flexible - PeopleLink's Multichannel Console DSP provides HD voice communications platform. This powerful, fault tolerant solution is ideal for the communication needs of large enterprises as well as Service providers looking to offer video conferencing services. Advanced design - This is the most powerful and up to date microphone Mixer, DSP and Amplifier available in the Industry today. It is Compact, Simple and extremely User-friendly allowing you to do Large scale Video Conferencing from a compact audio System.

key Features

- Range: Wide operating range of 100 feet
- Power Supply Safety: Power Supply Unit with Short Circuit, Overload and Over Voltage
 Protection
- SMT SMT Circuit: Surface Mount Technology (SMT) Circuit
- **Efficiency**: High efficiency of ~90%
- Current: Very low quiescent current. Can run on inverter.
- Circuit: Technology (SMT) Circuit Integrated Self-Protection Surface Mount
- Frequency lock: Quartz-locked frequency
- Area of application : Classrooms,
 Training Rooms
- Capacity: 40 to 60 seater
- Chassis: 19-Inch chassis 1.5U
 (Rack Mountable) DSP with Inbuilt amplifier with wireless microphone

 System



General Specifications

Wireless Microphone System

Frequency type: Quartz locked frequency

Operating Range: 100 Feet

Microphone Options: 2 x Handheld/ 1 Handheld +1

headband / 2 x headband Microphones

Frequencies : 5 non interfering frequencies available

Antennas : Soft, Flexible rubberised antennas

Output: Balanced Phoenix and Mixed Unbalanced 1/4"

Outputs

LCD Display: Frequency, Group, Antenna & Channel is

displayed on the LCD in the receiver

Gain Control: Separate gain controls for both the

channels

Microphone Frequency Response: 80 Hz-18KHz

Microphone Type: UHF

Amplifier

Power output @ 8 ohms: 2 X50W, Vcc= 24V DC

Minimum impedance: 8 ohms @50W

Frequency response: 20 Hz-20,000Hz

Operating supply voltage: 8 V to 24 V

Type: Class D (Digital)

Digital Signal Processor

Frequency Range: 30 Hz. to 16KHz.

Automatic Echo Cancellation: Yes

Automatic Gain Control: Yes

Dynamic Noise Reduction: Yes

Noise Supression: Yes

Full Duplex: Yes

Interface

Input: Built-In 1 x Handheld, 1 x headband

Microphone

Unbalanced MIC input: 1x 6.5mm phono jack with

gain controlle

Balanced 48v/12v phantom MIC inputs: 1x Phoenix

ports with separate gain controller

Line input: 1 x 2RCA

Line Output: 1 x 2RCA

USB Interface for PC connectivity : 1 x USB 2.0

RS-232 for controlling: 1x RS-232 audio controlling

Miscellaneous

Power Supply Unit (PSU): Power Supply Unit with Short Circuit, Overload and Over Voltage Protection

Application: Classrooms, Training Rooms

Capacity: 40 to 60 Seater

Shape of the room : Any

Packaging Information

Components: 19 inch chassis 1.5U (Rack Mountable)

with Inbuilt DSP


Package Includes: Inbuilt Package Includes People Link Multi Channel Console DSP with built-inAmplifier, Wireless Handheld Microphone, Wireless Headband Microphone, USB2.0x1,Cable, Stereo to Microphone, 2 RCA Cable x2, 50W Speakers x2







Device Set-up







Disclaimer:- Room setup diagrams provided for reference only. Actual room setup and size may vary as per requirements.



Ordering Information

PeopleLink Multichannel All in one DSP

: PPU-MCC-DSP-AIO

LEARN MORE

For more information on AIO DSP 100W Click Here

SALES AND INQUIRIES

Global Headquarters

Q3-A3, 10th Floor Cyber Towers, HITEC City, Hyderabad, Telangana 500081, India Phone: +91 9100123013 Email: vc@peoplelinkvc.com

International Contact Numbers

USA: +1 669-696-8383 Australia: +61 370 037070 France: +33 6 80 75 26 42 Middle East: +966 5300 19292 UK: +44 20 4571 5454

UAE: +971 559-002093 Canada: +1 647-945-7373 Malaysia: +(6)018-2872188 New Zealand: +64-9-802-4666

New Zealand: +64-9-802-Africa: +254 722 619 314

Tech Support

Toll Free: 1800 208 3399 customersupport@peoplelinkvc.

com

© 2024 All rights reserved PeopleLink. the PeopleLink logo and other PeopleLink marks are owned by PeopleLink and may be registered.